

ICY DOCK® EZConvert

M.2 NVMe SSD to 2.5" U.2 SSD Converter (7mm Height)



Cremax Europe GmbH
Email: support@icydock.com
Weidenweg 21H, 47059 Duisburg, Germany



Beyond Technologies UK Ltd
Email: info@beyondtech.co.uk
Unit B6, Halesfield 11, Telford, Shropshire, TF7 4PH, U.K.


Copyright © ICY DOCK International. All Rights Reserved. 650333 VER 1.0

1

Package Contents • Packungsinhalt • Contenu • Contenido del paquete
• 包装について • 包装説明 • 包装说明




Device



User manual




4 x M3*4 flat head screws
for device



1 x M.2 SSD Locking Clip

2

Device Information • Geräteinformationen • Informations dispositif
• Información del dispositivo • 本体説明 • 機體説明 • 机体说明




- 1 Heat sink cover
- 2 Thermal pad
- 3 U.2 connector
- 4 M.2 M-key connector
- 5 M.2 2280/2260/2242/2230 lock point (Default in 2280 lock point)
- 6 M.2 SSD locking clip
- 7 Cover screw holes

3


Installation Guide • Installationsanleitung • Guide d'Installation • Guía de instalación • 製品の組み込み手順について • 操作步驟 • 操作步驟

3-1




Grasp the two holes on heat sink cover and open as indicated by the arrow in the illustration.

3-2




A locking clip is fixed at the 2280 position. For 2280 M.2 SSDs, use the fixed clip. For 2230 / 2242 / 2260 SSDs, insert the included extra clip into the correct slot. Slide the clip backward to lock it in place or forward to remove it.

3-3




Insert the end of the M.2 SSD with the gold fingers into the M.2 connector on the drive tray at an angle, as shown in the illustration.

3-4




After inserting the SSD, press down on the end with the screw hole until the metal spring latch on the M.2 SSD locker snaps back into place, securing the M.2 SSD.

3-5




Remove the protective film from the thermal pad on the heat sink cover.

3-6



3-7



(Optional) Use the included M3*4 flat head screw to secure the heat sink cover with the M.2 adapter.

Recommended Usage and Compatibility Note:

To ensure the best performance and compatibility, we strongly recommend using ICY DOCK's certified cables and NVMe drive enclosures with this SSD converter. This minimizes the risk of signal loss or connection errors, especially under PCIe Gen 4/5 high-speed operations.

To explore compatible cables, host cards, and enclosures, please visit our NVMe Storage Selection Guide:

<https://global.icydock.com/nvmetool.html>



Warranty

[icydock.com/warranty](https://www.icydock.com/warranty)



Product Resources

Specs · Data Sheet · FAQ

ICY DOCK reserves the right to change product specifications, components, or accessories without prior notice